Evaluation of Large-Area, Low-Noise, Arrays of SiPMs

Tuesday, 19 May 2015 16:00 (1h 30m)

In this work we present the first evaluation results of an array of 12x12 SiPMs MicroFC-30035-SMT from SensL. These sensors are basically identical to those custom fabricated for the brain PET insert of the MindView project, except for the larger package. Both the C-Series and MindView parts are built with the same principle resulting on low dark noise contributions. These arrays cover an active area of approximately 5x5cm2 with a pitch of 4.2mm.

We have especially evaluated the 12x12 MicroFC array with monolithic scintillators. The new results are compared to former findings with the B-Series arrays. In the tests shown here, 10 mm thick black-painted crystals are used, which exit surface dimensions matches the photosensor active area. The photosensor blocks are always run at a stable temperature in the range of 20-22C (+/- 0.05C). Typical operation bias of the arrays was 30V, inferring about 600 kHz dark counts rate for each SiPM (67 kcps/mm2). A resistive readout has been designed to provide information for each row and column of the SiPMs matrix. Thus, 24 signals are being digitalized, with 250 ns integration time.

9x9 Na-22 collimated sources are used in the experiments. The sources have dimensions of 1mm in diameter and 1 mm height, and the collimators are 1.2mm aperture. Spatial resolution results (FWHM) along the crystal surface below 2.5mm, including source dimensions, have been found. These values are significantly improved compared to 3.5mm obtained with the B-Series in the past. At a distance of 20mm off-center, the system shows a negligible edge effect. These tests also showed a good energy resolution in the range of 16-17%.

Primary author: GONZALEZ, Antonio (Institute for Instrumentation in Molecular Imaging, i3M-CSIC)

Co-authors: Dr AGUILAR TALENS, Albert (Institute for Instrumentation in Molecular Imaging, i3M-CSIC); Dr SANCHEZ MARTINEZ, Filomeno (Institute for Instrumentation in Molecular Imaging, i3M-CSIC); Dr BENLLOCH BAVIERA, Jose Maria (Institute for Instrumentation in Molecular Imaging, i3M-CSIC); Mr HERNANDEZ HERNANDEZ, Liczandro (Institute for Instrumentation in Molecular Imaging, i3M-CSIC); Mr CONDE, Pablo (Institute for Instrumentation in Molecular Imaging, i3M-CSIC); Mr CONDE, Pablo (Institute for Instrumentation in Molecular Imaging, i3M-CSIC); Mr CONDE, Pablo (Institute for Instrumentation in Molecular Imaging, i3M-CSIC); Mr CONDE, Pablo (Institute for Instrumentation in Molecular Imaging, i3M-CSIC); Mr CONDE, Pablo (Institute for Instrumentation in Molecular Imaging, i3M-CSIC); Mr CONDE, Pablo (Institute for Instrumentation in Molecular Imaging, i3M-CSIC); Mr CONDE, Pablo (Institute for Instrumentation in Molecular Imaging, i3M-CSIC); Mr CONDE, Pablo (Institute for Instrumentation in Molecular Imaging, i3M-CSIC); Mr CONDE, Pablo (Institute for Instrumentation in Molecular Imaging, i3M-CSIC); Mr CONDE, Pablo (Institute for Instrumentation in Molecular Imaging, i3M-CSIC); Mr CONDE, Pablo (Institute for Instrumentation in Molecular Imaging, i3M-CSIC); Mr CONDE, Pablo (Institute for Instrumentation in Molecular Imaging, i3M-CSIC); Mr CONDE, Pablo (Institute for Instrumentation in Molecular Imaging, i3M-CSIC); Mr CONDE, Pablo (Institute for Instrumentation in Molecular Imaging, i3M-CSIC); Mr CONDE, Pablo (Institute for Instrumentation in Molecular Imaging, i3M-CSIC); Mr CONDE, Pablo (Institute for Instrumentation in Molecular Imaging, i3M-CSIC); Mr CONDE, Pablo (Institute for Instrumentation in Molecular Imaging, i3M-CSIC); Mr CONDE, Pablo (Institute for Instrumentation in Molecular Imaging, i3M-CSIC); Mr CONDE, Pablo (Institute for Instrumentation in Molecular Imaging, i3M-CSIC); Mr CONDE, Pablo (Institute for Instrumentation in Molecular Imaging, i3M-CSIC); Mr CONDE, Pablo (Institute for Instrumentation in Mole

Presenter: GONZALEZ, Antonio (Institute for Instrumentation in Molecular Imaging, i3M-CSIC)

Session Classification: Session 8 - Poster Session I

Track Classification: 1 - Advances in MR-PET instrumentation: detectors